

DATASHEET

MaNima HMI-TOUCHSCREEN



*Easy to use touch interface to control the
MaNima Digital LED Interface.*

Technical Specifications

The MaNima HMI-touchscreen is an easy to use fully customizable interface used to control the MaNima Digital LED Interface. Due to its optimised user interface, a user can control his lighting installation with ease.

Connections	4X USB, 1X Ethernet/LAN, 2X Micro-USB, 1X HDMI
Operation System	Linux
Touchscreen	Based on raspberry-pi
Possibility to customize the interface	Yes
IP Rating	IP20
Operation temperature	-25 ~ +70
Touch	Yes
Warranty	5 Years
Directives	<ul style="list-style-type: none"> • RoHS 2002/95/EC Compliant • EMC 2004/108/EC
Brand	MaNima Technologies
Dimmer / Controller	Controller Digital
DIN rail	No
Screen Dimensions	194mm x 110mm x 50mm
Viewable screen size	155mm x 86mm
Screen Resolution	800 x 480 pixels
Color	Black
Viewing angle	70°
RGB colour	24-bit

For a full description of the HMI-touchscreen, consult the manual.



Contact Info

MaNima Technologies BV

Address:

Hastelweg 260-B
5652 CN, Eindhoven
Netherlands

Contact:

Phone: +31 (0)40 243 08 80
E-mail: Info@Luxalight.eu
Website: www.Luxalight.eu

Dutch chamber of Commerce registration number/KvK-nummer: 71614605

